

MPO CASSETTE MODULES

MPO Cassette Module with 2 sizes in option. Preloaded with 12- or 24-Fiber MPO to LC hydra assemblies and LC adapters of customer specified fiber mode.

By integrating with Olabs' Plug-and-Play rackmount enclosure, this snap-in modularized MPO cassette offers seamless plug-and-play solution that improves cable manageability and supports quick installation.



KEY FEATURES :

- ▶ For integrating with Olabs Plug-and-Play Rackmount Enclosure
- ▶ Pre-loaded with MPO-Male to LC hydra assemblies and adapters on front and rear
- ▶ 12- or 24-Fiber count for options
- ▶ Installer friendly snap-in modular cassette design
- ▶ Reduce labour cost by eliminating field terminations
- ▶ Pre-installed with factory-terminated MPO to LC hydra assembly

Specifications

Main Material	Aluminum
Dimension	Size-A : 32mm x 120mm x 116mm
Height (H) x Width (W) x Depth (D)	Size-B : 32mm x 102mm x 116mm
Available Interface	MPO to LC
Fiber Count per Cassette	12-Fiber [preloaded with 1x12F MPO-Male assembly] 24-Fiber [preloaded with 1x24F or 2x12F MPO-Male assembly]
Available Fiber Modes	Singlemode [OS 1/2] Multimode [OM1, OM2, OM3, OM4]
Color & Coating	Black Powder Coating
Compliance	RoHS, EIA/ECA-310
Preloaded Units	MPO-Male hydra assemblies LC Adapter [in the front] MPO Adapter [at the rear] Channel Label and Data Label [printed on front and rear]

Optical Performance


MPO	Singlemode	IL ≤ 0.75dB, RL ≥ 50dB
	Multimode 50/125	IL ≤ 0.35dB, RL ≥ 25dB
LC	Singlemode	IL ≤ 0.30dB, RL ≥ 50dB
	Multimode 50/125	IL ≤ 0.30dB, RL ≥ 23dB

MPO CASSETTE MODULES

MPO CASSETTE MODULES

THE CASSETTE IS PRELOADED WITH MPO-MALE TO LC ASSEMBLIES, 3 FORMS OF MPO INTERFACE IS AVAILABLE FOR OPTIONS :


12-Fiber Cassette with 1x12F MPO interface



Preloaded with:

- 1x12F MPO-Male to 12xLC hydra Assembly
- 12-port of LC Adapters at front
- 1pc of MPO Adapter at rear


24-Fiber Cassette with 1x24F MPO interface



Preloaded with:


- 1x24F MPO-Male to 24xLC hydra Assembly
- 24-port of LC Adapter at front
- 1pc of MPO Adapters at rear

24-Fiber Cassette with 2x12F MPO interface



Preloaded with:

- 2pcs of 1x12F MPO-Male to 12xLC hydra Assembly
- 24-port of LC Adapter at front
- 2pcs of MPO Adapters at rear

SIZE-A CASSETTE

32(H) x 120(W) x 116(D) mm, this cassette is designed to fit into 3-slot Drawer [M3A-Drawer^[1], or to fit into 12-slot 4U Fixed Type-A PPM enclosure^[2].

(1) M3A-Drawer refers to Page 81


(2) 12-slot 4U Fixed Type-A PPM refers to Page 82

12-Fiber Cassette with 1x12F MPO interface



Item Description				Part No.
Fiber Count	Fiber Mode	Adapter Color on Front Panel	No. of MPO Adapter at the Rear	
12	OS1/OS2	Blue	1 [1 x 12F MPO]	PMA1SUD
12	OM1	Beige	1 [1 x 12F MPO]	PMA1M1D
12	OM2	Beige	1 [1 x 12F MPO]	PMA1M2D
12	OM3	Aqua	1 [1 x 12F MPO]	PMA1M3D
12	OM4	Aqua	1 [1 x 12F MPO]	PMA1M4D

CASSETTE FRONT



CASSETTE REAR



1pc of MPO Adapter at cassette rear


MPO CASSETTE MODULES

24-Fiber Cassette with 1x24F MPO interface



Item Description				Part No.
Fiber Count	Fiber Mode	Adapter Color on Front Panel	No. of MPO Adapter at the Rear	
24	OS1/OS2	Blue	1 (1 x 24F MPO)	PMA2SUD
24	OM1	Beige	1 (1 x 24F MPO)	PMA2M1D
24	OM2	Beige	1 (1 x 24F MPO)	PMA2M2D
24	OM3	Aqua	1 (1 x 24F MPO)	PMA2M3D
24	OM4	Aqua	1 (1 x 24F MPO)	PMA2M4D

CASSETTE FRONT



CASSETTE REAR




24-Fiber Cassette with 2x12F MPO interface



Item Description				Part No.
Fiber Count	Fiber Mode	Adapter Color on Front Panel	No. of MPO Adapter at the Rear	
24	OS1/OS2	Blue	2 (2 x 12F MPO)	PMA3SUD
24	OM1	Beige	2 (2 x 12F MPO)	PMA3M1D
24	OM2	Beige	2 (2 x 12F MPO)	PMA3M2D
24	OM3	Aqua	2 (2 x 12F MPO)	PMA3M3D
24	OM4	Aqua	2 (2 x 12F MPO)	PMA3M4D


CASSETTE FRONT



CASSETTE REAR



SIZE-B CASSETTE



32(H) x 102(W) x 116(D) mm, this cassette is designed to fit into 4-slot Drawer [M4B-Drawer]⁽¹⁾, or to fit into 12-slot 4U Fixed Type-B PPM enclosure⁽²⁾.

(1) M4B-Drawer refers to Page 81

(2) 12-slot 4U Fixed Type-B PPM enclosure refers to Page 82

MPO CASSETTE MODULES

MPO CASSETTE MODULES**SIZE-B CASSETTE**


12-Fiber Cassette with 1x12F MPO interface



CASSETTE FRONT

Item Description				Part No.
Fiber Count	Fiber Mode	Adapter Color on Front Panel	No. of MPO Adapter at the Rear	
12	OS1/OS2	Blue	1 (1 x 12F MPO)	PMB1SUD
12	OM1	Beige	1 (1 x 12F MPO)	PMB1M1D
12	OM2	Beige	1 (1 x 12F MPO)	PMB1M2D
12	OM3	Aqua	1 (1 x 12F MPO)	PMB1M3D
12	OM4	Aqua	1 (1 x 12F MPO)	PMB1M4D

CASSETTE REAR



1pc of MPO Adatper at cassette rear


24-Fiber Cassette with 1x24F MPO interface



CASSETTE FRONT

Item Description				Part No.
Fiber Count	Fiber Mode	Adapter Color on Front Panel	No. of MPO Adapter at the Rear	
24	OS1/OS2	Blue	1 (1 x 24F MPO)	PMB2SUD
24	OM1	Beige	1 (1 x 24F MPO)	PMB2M1D
24	OM2	Beige	1 (1 x 24F MPO)	PMB2M2D
24	OM3	Aqua	1 (1 x 24F MPO)	PMB2M3D
24	OM4	Aqua	1 (1 x 24F MPO)	PMB2M4D

CASSETTE REAR



1pc of MPO Adatper at cassette rear


24-Fiber Cassette with 2x12F MPO interface



CASSETTE FRONT

Item Description				Part No.
Fiber Count	Fiber Mode	Adapter Color on Front Panel	No. of MPO Adapter at the Rear	
24	OS1/OS2	Blue	2 (2 x 12F MPO)	PMB3SUD
24	OM1	Beige	2 (2 x 12F MPO)	PMB3M1D
24	OM2	Beige	2 (2 x 12F MPO)	PMB3M2D
24	OM3	Aqua	2 (2 x 12F MPO)	PMB3M3D
24	OM4	Aqua	2 (2 x 12F MPO)	PMB3M4D

CASSETTE REAR



2pcs of MPO Adatpers at cassette rear